Target Module Connection and Disconnection Procedure				
Document-141576	Release No. 3	Release Date.: 2019-10-23		

6 Module Connection Checklist

SEQ	ITEM	NOTE	CHECK
Safety	Acknowledge and Activate Work Permit	Call ISAC operators (x7500) Call Main Control Room if disconnecting or closing water supply/return in SEQ 0 (x 7333) or if supplied airhood is necessary	ok
Safety	Hold Pre-Job Briefing	 Discuss hazards, safety protocols and work steps listed in this document and checklists. All workers on the work permit shall be present. If there are concerns about the job, discuss with supervisors and re-plan if necessary. If you become contaminated during the job, contact the Main Control Room at x7333 for assistance. 	ok
Safety	 Electronic Dosimeter Tank Suit Respirator/Supplied Air Overshoes (double) Gloves(double) Safety Glasses / Full Face Respirator 	Remove and replace second pair of overshoes when exiting the pit to reduce risk of spreading contamination.	ok
Prep	Check tools: Hex Keys (3/16" & 3/8") Side Cutter Wipes 10" Cable Ties RAM		OK
Safety	Check with ISAC Ops re: alpha CAM reading P beam off for at least 30 min before entering target pit Check the General Field of ITW/ ITE	RAM or pole monitor (≤ 500 μSv/h)	ols
0	High Active Cooling Water	Verify valve for supply water closed Verify valve for return water closed	ok
1	Shutter	Cut cable tie	01

Target Module Connection and Disconnection Procedure				
Document-141576	Release No. 3	Release Date.: 2019-10-23		

SEQ	ITEM	NOTE	CHECK
		Push down bellow (air cylinder)	
2	Compressed Air to Shutter and Valves (x2)	Shutter should be opened (pushed down)	ok
3	Gas Line (5/8" & 11/16")	FEBIAD target only Two manual valves are opened	DK
4	ITW/ITE Roughing out	Ask ISAC operator rouging out ITW/ITE	OK
5	High Current Cables: a) (A)Target Oven + b) (B)Target Oven - c) (C)Tube heater - d) (D)Tube Heater + e) (T)60KV Bias f) (PQ)Coil + g) (RU)Coil -	f) FEBIAD target only g) FEBIAD target only	ok
6	Extraction Electrode (I)		010
7	Two 6-pin connectors (T,H)	Connect grounding wires to 60 kv bias	ok
8	Einzel Lens (Y)	Einzel lens cable should be routed as far away from all 60 kV corona rings as possible	ok
9	52 Pin Connector (H)	Ground to bias stand	OK
10	a) Water Lines 1. Target Oven 2. Tube Heater 3. MSP 4. EE 5. HS 6. Window 7. Coil 1 b) No Drip Leaks on Quick Connector (QC) c) No contact between SST Elbows and QC	a) Water Lines 1. With bypass loop between Ta+ and Ta- on module 2. With bypass loop between Tu+ and Tu- on module 3. Bypassed (looped) on station. Cable tie to station. 4. Connected to module always b) Open suppl and return valves 1. Hand check, wipe away water if necessary 2. SST elbows and quick connectors must be clear of each other, otherwise an electrical short will be produced.	ok

Target Module Connection and Disconnection Procedure					
Document-141576	Release Date.: 2019-10-23				

SEQ	ITEM	North	1
11	Vacuum System a) TP1 Controller b) TP2 Controller c) TP1 BV1 d) TP2 BV2 e) IG1 f) TP1 TP2 Fans	a) Connector on pump body b) Connector on pump body c) KF 25 and O-ring, Connector for BV 24 V DC d) KF 25 and O-ring, Connector for BV 24 V DC e) Align the gauge pins f) Attach and switch on all fans (2 of 110 V Plugs for ITW, switch on Extension bar for ITE)	CHECK
12	Steers ITE: Top Left Bottom (right) ITW: X Y Common	Top-X • Left-Y • Bottom (right) – Common ITW – TM4: • X-Top • Y-Left • Common – Bottom (Right)	ok.
13	ISAC Control Page set up (plug, connector)	Surface with EINZEL LENS, IGLIS, and	DIC
14	TP1 TP2 Controllers Reset	FEBIAD Electrical room, TP1 and TP2 controllers	VI
15	Water Signals Check a) Target Module: 1. Target, 2. Tube, 3. MSP 4. HS 5. EE 6. Coil (1) 7. Module Window b) Beamline 2A: 1. Tank 2. Dump (Plug) 3. Dump Shielding 4. 2A Window 5. Collimator	In Electrical room, water signal panels: Yellow lights should flick at certain frequency and green lights should be constantly on *If signal is not right, go back to pit and visually check wheel spin in flow sensor for trouble shooting TM2 and TM4 GE line are not in use (leak), No signal	ok
16	Double Check Module Connection	General, visually check all connections Verify voltage gaps free of cables and waterlines	ok

Target Module Connection and Disconnection Procedure				
Document-141576 Release No. 3 Release Date.: 2019-10-23				

SEQ	ITEM	NOTE	CHECK
17	HV Fence and HV Cover on TM Service Cap	Limit switches and cables Retract HV Keys	OK
18	Restore HV Keys to Electrical Room	Limit switches signals check in electrical room	ok
19	Start TP1 TP2	ITW/ITE: CG4/CG4S below 200 mTorr/ (ask ISAC OP)	ok
20	All Turbo Pumps(six) Current Draw Check at Normal Status	Check current draw for each pump on TP controller, current draw at full speed (38kRPM) ≤ 2.0 A Visually confirm TPBVs in pit are opened (red buttons stick out)	OK
21	Return Work Permit and E-log entry		Mark Hall

NOTES:

DATE: STARGET: TARGET MODULE: TMI
STATION: ITW ITE
SIGNATURE 1: WALLED TO THE STATE OF THE STATE TM3 TM4

SIGNATURE 2: